

Unit Ref	Nom Spd	dBA	Volume M3/s @ Pa Pressure											Input Pt	Current	Amps	Speed
			FID	25	50	75	100	125	150	175	200	250	300				
RU-Ebm-250-21	2500	60	0.381	0.330	0.247									0.14	0.6	2.4	B
RU-Ebm-250-41	1400	44	0.230	0.142										0.047	0.21	0.84	B
RU-ZAP-315-21	2650	61	0.868	0.768	0.713	0.680	0.642	0.601	0.561					0.47	2.1	6	A
RU-ZAP-315-41	1360	48	0.491	0.450	0.390	0.340	0.290							0.13	0.64	1.1	B
RU-ZAP-350-41	1330	53	0.666	0.540	0.550	0.500	0.448							0.19	0.84	1.45	B
RU-ZAP-350-61	910	44	0.388	0.155	0.109									0.1	0.5	100	B
RU-ZAP-400-41	1350	58	1.060	0.970	0.880	0.750	0.620							0.29	1.45	2.4	B
RU-ZAP-400-61	940	48	0.594	0.440	0.157									0.13	0.6	1.4	B
RU-ZAP-450-41	1370	58	1.110	1.040	0.820	0.740	0.680							0.36	1.6	3.6	A
RU-ZAP-450-61	930	49	0.840	0.682	0.480									0.17	0.75	1.5	B
RU-ZAP-500-41	1290	60	1.923	1.810	1.710	1.570	1.440	1.300	1.130					0.51	2.3	4.5	C
RU-ZAP-500-61	920	54	1.251	1.008	0.630	0.320								0.2	0.96	2.7	A
RU-ZAP-560-41	1300	68	2.311	2.133	2.060	1.900	1.548							1.6	7.5	15	C1
RU-ZAP-560-61	880	55	1.364	1.159										0.43	1.95	4.6	A
RU-ZAP-630-61	880	59	2.465	2.200	1.523	1.240	0.924							0.6	2.7	5.3	A
RU-ZAP-630-81	650	55	1.666	1.426	0.727									0.32	1.45	3.1	A
RU-ZAP-710-61	850	61	2.940	2.710	2.125									0.89	4.1	8	C
Three Phase Units																	
RU-ZAP315-23	2690	64	0.868	0.768	0.713	0.680	0.642	0.601	0.561					0.51	0.79	2.4	D
RU-ZAP315-43	1390	48	0.545	0.431	0.364	0.282								0.11	0.27	0.85	D
RU-ZAP350-43	1390	54	0.652	0.537	0.464									0.18	0.39	1.35	D
RU-ZAP350-63	910	44	0.400	0.155	0.109									0.09	0.25	0.75	D
RU-ZAP-400-43	1380	59	1.019	0.893	0.782	0.711	0.610	0.461						0.28	0.6	2.1	D
RU-ZAP-400-63	920	48	0.594	0.440	0.157									0.11	0.28	0.9	D
RU-ZAP-450-43	1390	58	1.265	1.189	1.120	1.033	0.946							0.36	0.75	2.6	D
RU-ZAP-450-63	940	49	0.840	0.682	0.463									0.125	0.35	1	D
RU-ZAP-500-43	1380	61	1.962	1.835	1.714	1.593	1.515	1.420	1.338					0.55	1.05	3.7	D
RU-ZAP-500-63	920	52	1.539	1.350	1.200	1.075								0.2	0.56	1.5	D
RU-ZAP-560-43	1300	63	2.308	2.217	2.000	1.650	1.505	1.398	1.280	1.189				1	1.8	7	E
RU-ZAP-560-63	860	55	1.436	1.189	0.800	0.635	0.400	0.200						0.39	0.81	1.75	D
RU-ZAP-630-43	1360	70	3.881	3.736	3.591	3.433	3.276	3.148	3.028	2.749	2.438			1.9	3.2	14	E
RU-ZAP-630-63	880	60	2.302	1.965	1.763	1.150	0.750							0.7	1.5	3.6	D
RU-ZAP-630-83	630	55	1.797	1.476	1.090									0.31	0.65	2	D
RU-ZAP-710-43	1350	70	5.890	5.700	5.540	5.360	5.170	4.900	4.750					2.9	4.9	23	F
RU-ZAP-710-63	890	62	3.050	2.634	2.326	1.910								0.89	1.8	6.4	D
RU-ZAP-710-83	640	55	2.339	1.630	1.133									0.42	1.1	3.3	D
RU-ZAP-800-63	900	62	4.700	4.450	4.170	3.890	3.600	3.020	2.500	2.180				1.4	2.7	9.8	E
RU-ZAP-100-63	935	78	11.00	10.81	10.60	10.20	9.60	9.10	8.12	7.35	6.85	5.56		5.5	10.5	67	
1Ph Speed controllers		A: SC3 \ RTRE3					B: SC1.5 \ RTRE1.5										
		C: SC5 \ RTRE5					C1:RTRE7										
3 Ph Speed controllers		D: RTRD2					E: RTRD4										
		F: RTRD7															